



**Verizon NEBS™ Compliance: Energy Efficiency  
Requirements for Telecommunications  
Equipment**  
Verizon Technical Purchasing Requirements  
VZ.TPR.9205  
**Issue 5, October 2011**



**CHANGE CONTROL RECORD:**

<b>Version</b>	<b>Date</b>	<b>Action*</b>	<b>Reason for Revision</b>
1	6/5/2008	New	New document.
2	6/12/2008	Add	Added text to describe weighting values
3	9/23/2008	Add	Added baseline values for BTS equipment Added Point-to-point Microwave requirements Added Set Top Box requirements
4	8/7/2009	Add	Power equipment category expanded to include inverters and converters Add Media Gateway category Update External Power Adapter section Add ONT Power Supplies to CPE section
5	10/6/2011	Add	Adoption of ATIS methodology for Transport, Ethernet Switch, Server and Rectifiers Add Digital Content Manager to Video Equipment category Add Soft Switch to Switch/Router category Add Automated Distribution Frame category
* New, Add, Delete, Change, Reissue			

**PREPARED BY:**

Name, Title, Organization	Date
<b>Todd Talbot</b> DMTS, NEBS, Fiber and Energy Efficiency Corporate Technology Systems Integration and Testing 320 St. Paul Place, Floor 14 Baltimore, MD 21202 Phone: 410-736-5945; Fax: 410-736-5144 E-mail: <a href="mailto:todd.f.talbot@verizon.com">todd.f.talbot@verizon.com</a>	10/6/2011

**APPROVED BY:**

Name, Title, Organization	Date
<b>Howard Davis</b> Manager, NEBS, Fiber and Energy Efficiency Corporate Technology Systems Integration and Testing 320 St. Paul Place, Floor 14 Baltimore, MD 21202 Phone: 410-736-5906; Fax: 410-736-5144 E-mail: <a href="mailto:howard.davis@verizon.com">howard.davis@verizon.com</a>	10/6/2011

# Table of Contents

1.0	<b><u>PURPOSE</u></b> .....	5
2.0	<b><u>SCOPE</u></b> .....	5
3.0	<b><u>REFERENCES</u></b> .....	5
4.0	<b><u>ACRONYMS</u></b> .....	6
5.0	<b><u>DEFINITIONS</u></b> .....	6
6.0	<b><u>EXAMPLES OF EQUIPMENT TYPES</u></b> .....	7
7.0	<b><u>TEER METHODOLOGY</u></b> .....	7
8.0	<b><u>SPATIAL REQUIREMENTS</u></b> .....	8
9.0	<b><u>GENERAL CONDITIONS FOR MEASUREMENT</u></b> .....	8
10.0	<b><u>MEASUREMENT APPROACH</u></b> .....	9
11.0	<b><u>TEER FORMULATION</u></b> .....	12
12.0	<b><u>CPE EQUIPMENT</u></b> .....	14
13.0	<b><u>EFFECTIVE DATE</u></b> .....	16
14.0	<b><u>TEST REPORT</u></b> .....	16

## 1.0 PURPOSE

The purpose of this Technical Purchasing Requirement (TPR) document is to provide a Telecommunications Equipment Energy Efficiency Rating (TEEER) methodology for procuring equipment assemblies used in Verizon's telecommunications networks. The intent is to foster the creation of more energy efficient telecommunications equipment by Verizon's supplier community thereby reducing the energy requirements in Verizon networks.

## 2.0 SCOPE

This TPR document provides the test methodology for calculating the TEEER to be used by Verizon in evaluating the supplier's equipment. This methodology is applicable to but not limited to shelf, frame and cabinet mounted DC powered network equipment to be installed in environmentally controlled environments and equipment located at the customer premises. AC powered customer premises equipment (CPE) and AC powered data center type equipment shall also be covered in this TPR.

## 3.0 REFERENCES

<b>GR-63-CORE</b>	NEBS™ Requirements: Physical Protection
<b>VZ.NEBS.TE.NPI.2004.015</b>	TCG Network Equipment Building Systems (NEBS) Compliance Checklist
	ENERGY STAR® Program Requirements for Set-Top Boxes Version 2.0
<b>ATIS-0600015.2009</b>	Energy Efficiency for Telecommunication Equipment: Methodology for Measurement and Reporting – General Requirements
<b>ATIS-0600015.01.2009</b>	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting - Server Requirements
<b>ATIS-0600015.02.2009</b>	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting – Transport Requirements
<b>ATIS-0600015.03.2009</b>	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting for Router and Ethernet Switch
<b>ATIS-0600015.04.2010</b>	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting DC Power Plant – Rectifier Requirements

## 4.0 ACRONYMS

<b>BHCA</b>	Busy Hour Call Attempts
<b>BBU</b>	Battery Back-up Unit
<b>BTS</b>	Base Transceiver Subsystem
<b>CPE</b>	Customer Premises Equipment
<b>DC</b>	Direct Current
<b>DCM</b>	Digital Content Manager
<b>DSLAM</b>	Digital Subscriber Line Access Multiplexer
<b>EUT</b>	Equipment Under Test
<b>OLT</b>	Optical Line Termination
<b>ONT</b>	Optical Network Terminal
<b>OPSU</b>	ONT Power Supply Unit
<b>STB</b>	Set-Top Box
<b>TEEER</b>	Telecommunication Equipment Energy Efficiency Rating
<b>TPR</b>	Technical Purchasing Requirement

## 5.0 DEFINITIONS

### 5.1 **TEEER**

A calculated value representing the energy efficiency rating of a specific product.

### 5.2 **Forwarding Capacity**

The number of bits per second that a device can be observed to transmit successfully to the correct egress interface.

### 5.3 **$P_{max}$**

The measured input power with the EUT operating at maximum load.

### 5.4 **$P_{sleep}$**

The measured input power of the EUT while operating in a sleep/no activity mode.

### 5.5 **$P_{Total}$**

The weighted total input power to be used in the formation of the TEEER value.

### 5.6 **$P_{50}$**

The measured input power of the EUT while operating at 50% of maximum load.

## 5.7 **Throughput**

The number of bits passing through the data communication system expressed in bits per second.

## 5.8 **TPR**

Verizon document defining the minimum requirements for the purchase of telecommunications equipment for NEBS compliance.

## 6.0 **EXAMPLES OF EQUIPMENT TYPES**

The following list provides examples of types of equipment that this TPR document covers. Other equipment not specifically listed will also be required to be tested to this document where applicable.

**Transport** – Optical, Video & Point-to-Point Microwave

**Router/Switch** – Edge Router, Core Router, Ethernet Switch & Soft Switch

**Gateway** – Media Gateway

**Access** – DSLAM & OLT

**Power** – Rectifier, Converter, Inverter & Uninterruptable Power Supply

**Video** – Digital Content Manager

**IT** – Server

**CPE** – Set-Top Box & ONT Power Supplies

**Wireless** – Power Amplifiers

## 7.0 **TEEER METHODOLOGY**

The table below shall be used in determining the proper methodology to be used in determining the TEEER value.

Table 1: TEEER Methodology

<b>Equipment Type</b>	<b>Methodology</b>
Server	ATIS-0600015.2009 / ATIS-0600015.01.2009
Transport	ATIS-0600015.2009 / ATIS-0600015.02.2009
Router and Ethernet Switch	ATIS-0600015.2009 / ATIS-0600015.03.2009
Rectifier	ATIS-0600015.2009 / ATIS-0600015.04.2009
All others	Per this TPR

Note – For equipment types not specifically addressed in this TPR, please contact the author of this document for further discussion.

## 7.1 ATIS Correction Factors

In order to align the ATIS TEER values with the Verizon Pass/Fail requirements, perform the following correction factor to the ATIS TEER value to obtain the Verizon TEEER value.

Table 2: Correction Factor

Equipment Type	Correction Factor
Server	ATIS TEER / 10
Transport	$-\log (1 / (\text{ATIS TEER} * 1000000))$
Router and Ethernet Switch	$-\log (1 / (\text{ATIS TEER} * 1000000000))$
Rectifier	ATIS TEER / 100

## 8.0 SPATIAL REQUIREMENTS

This document supersedes all other documents with respect to equipment sizing in Verizon's network

In order to mitigate high-density equipment and promote energy efficiency, Verizon will accept equipment with the following maximum nominal sizes.

Height = 7 feet

Width = 23 inches (typical rack width)

Depth = 36 inches

Equipment with dimensions greater than what is listed above will be handled on a case by case basis.

## 9.0 GENERAL CONDITIONS FOR MEASUREMENT

### 9.1 General

Testing is to be performed at or witnessed by a Verizon approved ITL as found on the Verizon NEBS webpage [www.verizonnebs.com](http://www.verizonnebs.com).

### 9.2 Environmental Criteria

#### 9.2.1 Temperature

The equipment shall be evaluated at a temperature of  $25^{\circ}\text{C} \pm 3^{\circ}\text{C}$

#### 9.2.2 Humidity

The equipment shall be evaluated at a relative humidity of 30% to 75%

#### 9.2.3 Pressure

The equipment shall be evaluated at site pressure between 1020 to 812 mbar

### 9.3 Test Equipment and Set-up

Power measurements shall be made with a suitably calibrated voltmeter and ammeter, or power analyzer. The power measurement instrument shall have a resolution of 0.1W or better for active power. Power measurements shall be taken immediately adjacent to the powered product being evaluated. Support equipment shall be provided to verify proper operation of the equipment under test.

### 9.4 Test Voltage

#### 9.4.1 DC Powered Equipment

The input to the EUT shall be at a DC voltage of  $-53V \pm 1.0V$ .

Equipment using voltages other than -48Vdc shall be evaluated at 2% of its nominal voltage.

#### 9.4.2 AC Powered Equipment

The input to the EUT shall be the specified voltage  $\pm 1\%$  and the specified frequency  $\pm 1\%$ .

## 10.0 MEASUREMENT APPROACH

### 10.1 Utilization Conditions

EUT shall be configured as a typical installation for Verizon. The equipment shall be fully loaded with all card slots populated with functioning modules and all redundancies in place. The equipment shall have all cables installed as in a typical deployment. All system functions or features that increase power consumption shall be activated during testing. If the equipment has any energy saving features that are controlled by internal software then they should be enabled for testing. The EUT shall be tested at the following utilization conditions unless specified otherwise:

**Table 3: Utilization Conditions for EUT**

Percentage of Utilization	
Utilization Condition 1	100%
Utilization Condition 2	50%
Utilization Condition 3	0%

Utilization Condition 1 shall be defined by the equipment manufacturer and based on the type of equipment to represent a 100% duty cycle.

Utilization Condition 2 shall represent a 50% duty cycle.

Utilization Condition 3 shall represent a 0% duty cycle. The equipment will be powered but performing no useful work (idle/sleep mode).

\*Note – For power equipment and mechanized distributing frames, please refer to the utilization conditions in their corresponding sections.

## 10.2 Testing Sequence

With the equipment configured as stated above, the EUT shall be operated at 100% utilization for at least 15 minutes prior to conducting power measurements.

After the 15 minute initialization period, the EUT input power shall be monitored as outlined in Section 8.3 to assess the stability of the EUT. If the power level does not drift by more than 5% from the maximum value observed, the EUT can be considered stable and the measurements can begin.

With the equipment operating under normal maximum power conditions, record the average input power to the equipment under test over a 15-minute time period for Utilization Condition 1. This value shall be recorded as  $P_{\max}$ .

Repeat power input measurements for Utilization Condition 2 and Utilization Condition 3 and record these values at  $P_{50}$  and  $P_{\text{sleep}}$  respectively.

The total power consumption for the EUT shall be represented by the weighting formula

$$P_{\text{Total}} = (0.35 \times P_{\max}) + (0.4 \times P_{50}) + (0.25 \times P_{\text{sleep}})$$

Where  $P_{\max}$  is the average power measured during Utilization Condition 1,  $P_{50}$  is the average power measured during Utilization Condition 2 and  $P_{\text{sleep}}$  is the average power measured during Utilization Condition 3.

## 10.3 Weighting Values

Verizon assigned weighting values to accommodate for the variable utilization of equipment in each duty cycle. Because typical telecommunications equipment in the field does not run at a constant duty cycle rate it was necessary to assign the values in the weighting formula listed in Section 10.2. Each weighting has been assigned a specific value based on Verizon's knowledge and experience of the operations of telecommunications equipment within its network. Typical Switching equipment runs nearest to the 50% utilization point and thus was given the greatest weighting in the formula. Although most telecommunications equipment does not have an idle/sleep mode, a relatively high weighting value was given as this may be the area of greatest savings in terms of reduced power consumption.

## 10.4 Power Equipment

### 10.4.1 General

Equipment is to be configured as would be for a typical Verizon deployment. Input power measurements shall be taken immediately adjacent to the input terminals. Output measurements shall be taken from the main output distribution bus. Breakers and fuses shall not be included for the calculations and measurements.

### 10.4.2 Power Utilization Levels

Power Equipment testing will be performed at utilization levels of 100% and 50%.

$$P_{\text{Out Total}} = (P_{\text{Out max}} + P_{\text{Out 50}})/2$$

$$P_{\text{In Total}} = (P_{\text{In max}} + P_{\text{In 50}})/2$$

## 10.5 Mechanized Distributing Frames

### 10.5.1 Power Utilization Levels

Mechanized Distributing Frames testing will be performed at utilization levels of  $P_{\text{idle}}$  and  $P_{\text{active}}$ .

$$P_{\text{Total}} = (0.75 \times P_{\text{idle}}) + (0.25 \times P_{\text{active}})$$

Where  $P_{\text{idle}}$  is the total consumed power over a 1 hour period and  $P_{\text{active}}$  is the total power consumed over a 1 hour period while making 50 cross connections. Power measurements are to be in kWh.

## 11.0 TEEER FORMULATION

### 11.1 TEEER Formulas

The total average power,  $P_{Total}$ , calculated from above, will be used in the calculation of the TEEER. Using the type of equipment that most closely resembles the equipment tested calculate the TEEER for the given system.

**Table 4: TEEER Formulas**

<b>Equipment Type</b>	<b>TEEER Formula</b>
Soft Switch	$-\log(P_{Total} / BHCA)$
Media Gateway	$-\log(P_{Total} / \text{Throughput})$
Video Multiplexer - DCM	$-\log(P_{Total} / \text{Throughput})$
Access	$(\text{Access Lines} / P_{Total}) + 1$
Power	$(P_{Out Total} / P_{In Total}) \times 10$
Power Amplifiers (Wireless)	$(\text{Total RF Output Power} / \text{Total Input Power}) \times 10$
Mechanized Distributing Frames	$-\log(P_{Total} / \# \text{ of input connections})$

Note: Round the TEEER value to the nearest hundredth decimal point

The TEEER value calculated as described above is a number that represents an energy efficiency rating on a scale of 1 to 10, with 1 representing the lowest energy efficiency rating and 10 representing the highest.

## 11.2 Verizon's Minimum TEEER Pass/Fail Requirements

The TEEER value calculated from above shall meet the minimum TEEER value allowable as defined in Table 3.

The below pass/fail criteria are based on averages of typical equipment located in Verizon equipment spaces with an additional 20% improvement value.

**Table 5: Pass/Fail Criteria**

<b>Equipment Type</b>	<b>Minimum TEEER Allowable</b>
Transport	7.54
Optical and Video	7.54
Point-to-Point Microwave	5.75
Switch/Router	7.67
Soft Switch	2.75
Media Gateway	6.54
Video Multiplexer	6.80
Access	2.50
Power	9.20
Rectifier	9.20
Converter	9.10
Inverter	9.00
Power Amplifier (Wireless)	1.05
Mechanized Distributing Frames	4.01

## 12.0 CPE EQUIPMENT

### 12.1 Set-Top Boxes

Set-Top Box equipment efficiency shall follow the methods and procedures of the most current version of the ENERGY STAR<sup>®</sup> requirements for Set-Top Boxes. ENERGY STAR<sup>®</sup> requirements for Set-Top Boxes can be found at the following website ([www.energystar.gov](http://www.energystar.gov)). A Set-Top Box model must meet or exceed a minimum average efficiency for base functionality (see Table 6), plus allowances for specific, additional functionalities (see Table 7) present across a duty cycle.

To calculate the allowance for a given device, the sum of the base functionality allowance and all applicable additional functionalities allowances are added. This value is compared to the measured values following the procedures as stated in the ENERGY STAR<sup>®</sup> Set-Top Box test procedures to determine compliance.

**Table 6: Base Functionality Annual Energy Allowance**

<b>Base Functionality</b>	<b>Tier 1 Annual Energy Allowance (kWh/year)</b>
Cable	70
Satellite	88
IP	45
Terrestrial	27
Thin-Client/Remote	27

**Table 7: Additional Functionality Annual Energy Allowance**

<b>Additional Functionalities</b>	<b>Tier 1 Annual Energy Allowance (kWh/year)</b>
Additional Tuners	53
Additional Tuners – Terrestrial/IP	14
Adv. Video Processing	18
DVR	60
High Definition	35
Removable Media Player	12
Removable Media Player/Recorder	23
Multi-Room	44
CableCard	15
Home Network Interface	20

**Example:** High Definition, Cable Set-top Box with DVR

Annual Energy Allowance (kWh/year) = Base Functionality + Additional Functionalities

Annual Energy Allowance (kWh/year) = 70 + 60 + 35

Annual Energy Allowance (kWh/year) = 165

## 12.2 ONT Power Supplies

### 12.2.1 General

Equipment is to be configured as would be for a typical Verizon deployment. Input power measurements shall be taken immediately adjacent to the input terminals of the OPSU. Output measurements shall be taken immediately adjacent to the output terminal of the BBU. A resistive load may be used to represent the ONT. Testing will be performed with the battery in a fully charged state.

### 12.2.2 ONT Power Supply Load Levels

ONT Power Supply testing will be performed at load levels of 100% and 50%.

$$P_{\text{Out Total}} = (P_{\text{Out max}} + P_{\text{Out 50}})/2$$

$$P_{\text{In Total}} = (P_{\text{In max}} + P_{\text{In 50}})/2$$

**Table 8: ONT Power Supply TEEER Formation**

<b>Equipment Type</b>	<b>TEEER Formula</b>
ONT Power Supply	$(P_{\text{Out Total}} / P_{\text{In Total}}) \times 10$

The TEEER value calculated from above shall meet the minimum TEEER value allowable as defined in Table 12.

**Table 9: Pass/Fail Criteria**

<b>Equipment Type</b>	<b>Minimum TEEER Allowable</b>
ONT Power Supply	7.20

### **13.0 EFFECTIVE DATE**

The effective date of this TPR shall be June 5, 2008. On January 1, 2009, all equipment provided to Verizon shall meet the minimum TEEER values as described in this document.

### **14.0 TEST REPORT**

A test report shall be prepared that contains all necessary information:

- Date and location of test
- Physical equipment configuration
- Software Version operating on system
- Equipment physical dimensions
- Activated features and functions during testing
- Non-activated features and functions during testing
- Explanation of configuration chosen/tested
- Description of equipment's functionality verification
- Support equipment used to verify operation of equipment
- Description of test equipment used for making measurements with calibration dates
- Deviations from standard
- Duration of input energy measurement
- $P_{idle}$ ,  $P_{max}$ ,  $P_{50}$  and  $P_{Total}$
- Telecommunication Equipment Energy Efficiency Rating (TEEER)
- All recorded test data

A sample Test Report Format can be found on the following pages.

# Appendix A

## Verizon TEEER Compliance Report

**CUSTOMER NAME:**

Company Name  
Company Address  
Company City, State

**PRODUCT:**

Product Name  
Product Model Number

**TESTED TO:**

Verizon Technical Purchasing Requirement  
VZ.TPR.9205, Issue 1, June 5, 2008

Date:

Report Number:

**VERIZON INDEPENDENT TESTING  
LABORATORY**

XYZ Lab  
Address  
City, State

Issued By: \_\_\_\_\_

Date: \_\_\_\_\_

Lab Director: \_\_\_\_\_

Date: \_\_\_\_\_

## Executive Summary

The **Vendor Name, Equipment Name, Model Number**, as submitted, was evaluated to VZ.TPR.9205, Telecommunications Energy Efficiency Rating, Issue 1. The **Equipment Name, Model Number** was found to have a TEEER of **X.XX**. The **Equipment Name, Model Number** conforms/does not conform to the requirements of VZ.TPR.9205.

## Test Data

Product:	
Vendor:	
Test Technician:	
Test Location:	
Test Date:	

<b>TEEER:</b>	
$P_{Total}$ :	
$P_{max}$ :	
$P_{50}$ :	
$P_{Sleep}$ :	
Throughput, Forwarding Capacity or Access Lines:	

<b>Equipment Under Test</b>	
<b>Hardware Configuration</b>	
Slot 1:	
Slot 2:	
Slot 3:	
Slot N:	
<b>Equipment Dimensions</b>	
Height:	
Width:	
Depth:	
<b>Software</b>	
Firmware version:	
Activated Features or Functions:	Disabled Features or Functions

<b>Environmental Test Conditions</b>		
Criteria	Start of Test	End of Test
Start Time		
Ambient Temperature:		
Humidity:		
Pressure:		
Feed Voltage:		
Supply Current:		
<b>Test Equipment</b>		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
<b>Support Equipment</b>		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		

Calculations:

Other Notes:

Photos of Test Set-up:

# Appendix B

## Examples of TEEER Formulations

### Media Gateway

$$\text{Throughput} = 980 \text{ Gbps}$$

$$P_{\max} = 300 \text{ W}$$

$$P_{50} = 280 \text{ W}$$

$$P_{\text{sleep}} = 250 \text{ W}$$

$$P_{\text{Total}} = (0.35 \times 300) + (0.4 \times 280) + (0.25 \times 250) = 279.5 \text{ W}$$

$$\begin{aligned} \text{TEEER} &= -\log (P_{\text{Total}} / \text{Throughput}) \\ &= -\log (279.5 / 980,000,000) \\ &= -\log (0.0000002852) \\ &= 6.54 \end{aligned}$$

### Access

$$\text{Access Lines} = 284$$

$$P_{\max} = 120 \text{ W}$$

$$P_{50} = 80 \text{ W}$$

$$P_{\text{sleep}} = 40 \text{ W}$$

$$P_{\text{Total}} = (0.35 \times 120) + (0.4 \times 80) + (0.25 \times 40) = 84 \text{ W}$$

$$\begin{aligned} \text{TEEER} &= (\text{Access Lines} / P_{\text{Total}}) + 1 \\ &= (284 / 84) + 1 \\ &= 4.38 \end{aligned}$$

### Power

$$P_{\text{Out max}} = 800 \text{ W}$$

$$P_{\text{Out 50}} = 400 \text{ W}$$

$$P_{\text{In max}} = 844 \text{ W}$$

$$P_{\text{In 50}} = 462 \text{ W}$$

$$P_{\text{Total Out}} = (800 + 400)/2 = 600$$

$$P_{\text{Total In}} = (838 + 462)/2 = 650$$

$$\begin{aligned} \text{TEEER} &= (P_{\text{Total Out}} / P_{\text{Total In}}) \times 10 \\ &= (600 / 650) \times 10 \\ &= 9.23 \end{aligned}$$

## **Power Amplifiers (Wireless)**

Sectors = 3

Carriers = 8

RF Output Power/Carrier, measured at the input of the Antenna P1= 20.0W

Input Power/Watt of output power P2 = 11.425W

Total Input Power for 3 Sector, 8 Carriers Amplification = Sectors x Carriers x P1 x P2

$$= 3 \times 8 \times 20 \times 11.425 \text{ W}$$

$$= 5484 \text{ W}$$

Total RF Output Power for 3 Sector, 8 Carriers = Sectors x Carriers x P1

$$= 3 \times 8 \times 20 \text{ W}$$

$$= 480 \text{ W}$$

TEEER = (Total RF Output Power / Total Input Power) x 10

$$= 480 / 5458 \times 10$$

$$= 0.875$$