

**Verizon NEBS[™] Compliance: Energy Efficiency
Requirements for Telecommunications
Equipment**
Verizon Technical Purchasing Requirements
VZ.TPR.9205
Issue 6, March 2016

CHANGE CONTROL RECORD:

Version	Date	Action*	Reason for Revision
1	6/5/2008	New	New document.
2	6/12/2008	Add	Added text to describe weighting values
3	9/23/2008	Add	Added baseline values for BTS equipment Added Point-to-point Microwave requirements Added Set Top Box requirements
4	8/7/2009	Add	Power equipment category expanded to include inverters and converters Add Media Gateway category Update External Power Adapter section Add ONT Power Supplies to CPE section
5	10/6/2011	Add	Adoption of ATIS methodology for Transport, Ethernet Switch, Server and Rectifiers Add Digital Content Manager to Video Equipment category Add Soft Switch to Switch/Router category Add Automated Distribution Frame category
6	1/31/16	Add	Adoption of ATIS methodology for Wireline Access Equipment, Small Network Equipment, Base Station and Inverters.
* New, Add, Delete, Change, Reissue			

Trademark Acknowledgement – NEBS is a trademark of Telcordia Technologies, Inc.

PREPARED BY:

Name, Title, Organization	Date
Todd Talbot DMTS – Maintenance Engineering - NEBS Verizon Wireline Network Operations 320 St. Paul Place, Floor 14 Baltimore, MD 21202 Phone: 410-736-5945 E-mail: todd.f.talbot@verizon.com	3/31/2016

APPROVED BY:

Name, Title, Organization	Date
David Hampton Manager - Maintenance Engineering Verizon Wireline Network Operations 1201 E Arapaho Road Richardson, Texas 75081 E-mail: david.hampton@one.verizon.com	3/31/2016

Table of Contents

1.0	PURPOSE	5
2.0	SCOPE	5
3.0	REFERENCES	5
4.0	ACRONYMS	6
5.0	DEFINITIONS	6
6.0	TEEER METHODOLOGY	7
7.0	GENERAL CONDITIONS FOR MEASUREMENT	8
8.0	MEASUREMENT APPROACH	8
9.0	TEEER FORMULATION	11
10.0	CPE EQUIPMENT	12
11.0	EFFECTIVE DATE	12
12.0	TEST REPORT	12

1.0 PURPOSE

The purpose of this Technical Purchasing Requirement (TPR) document is to provide a Telecommunications Equipment Energy Efficiency Rating (TEEER) methodology for procuring equipment assemblies used in Verizon's telecommunications networks. The intent is to foster the creation of more energy efficient telecommunications equipment by Verizon's supplier community thereby reducing the energy requirements in Verizon networks.

2.0 SCOPE

This TPR document provides the test methodology for calculating the TEEER to be used by Verizon in evaluating the supplier's equipment. This methodology is applicable to but not limited to shelf, frame and cabinet mounted DC powered network equipment to be installed in environmentally controlled environments and equipment located at the customer premises. Some AC powered equipment shall also be covered in this TPR.

3.0 REFERENCES

GR-63-CORE	NEBS™ Requirements: Physical Protection
VZ.NEBS.TE.NPI.2004.015	TCG Network Equipment Building Systems (NEBS) Compliance Checklist
	ENERGY STAR® Program Requirements for Set-Top Boxes
ATIS-0600015.2013	Energy Efficiency for Telecommunication Equipment: Methodology for Measurement and Reporting – General Requirements
ATIS-0600015.01.2014	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting - Server Requirements
ATIS-0600015.02.2014	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting – Transport Requirements
ATIS-0600015.03.2013	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting for Router and Ethernet Switch
ATIS-0600015.04.2010	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting DC Power Plant – Rectifier Requirements
ATIS-0600015.07.2013	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting Wireline Access, Asymmetric Broadband Equipment
ATIS-0600015.08.2014	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting for Small Network Equipment
ATIS-0600015.09.2015	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting of Base Station Metrics

ATIS-0600015.10.2015	Energy Efficiency for Telecommunications Equipment: Methodology for Measurement and Reporting DC Power Plant – Inverter Requirements
-----------------------------	--

4.0 ACRONYMS

BHCA	Busy Hour Call Attempts
BBU	Battery Back-up Unit
BTS	Base Transceiver Subsystem
CPE	Customer Premises Equipment
DC	Direct Current
DCM	Digital Content Manager
DSLAM	Digital Subscriber Line Access Multiplexer
EUT	Equipment Under Test
OLT	Optical Line Termination
ONT	Optical Network Terminal
OPSU	ONT Power Supply Unit
STB	Set-Top Box
TEEER	Telecommunication Equipment Energy Efficiency Rating
TPR	Technical Purchasing Requirement

5.0 DEFINITIONS

5.1 **TEEER**

A calculated value representing the energy efficiency rating of a specific product.

5.2 **Forwarding Capacity**

The number of bits per second that a device can be observed to transmit successfully to the correct egress interface.

5.3 **P_{max}**

The measured input power with the EUT operating at maximum load.

5.4 **P_{sleep}**

The measured input power of the EUT while operating in a sleep/no activity mode.

5.5 **P_{Total}**

The weighted total input power to be used in the formation of the TEEER value.

5.6 **P_{50}**

The measured input power of the EUT while operating at 50% of maximum load.

5.7 Throughput

The number of bits passing through the data communication system expressed in bits per second.

5.8 TPR

Verizon document defining the minimum requirements for the purchase of telecommunications equipment for NEBS compliance.

6.0 TEEER METHODOLOGY

The table below shall be used in determining the proper methodology to be used in determining the TEEER value.

Table 1: TEEER Methodology

Equipment Type	Methodology
Server	ATIS-0600015.2013 / ATIS-0600015.01.2014
Transport	ATIS-0600015.2013 / ATIS-0600015.02.2014
Router and Ethernet Switch	ATIS-0600015.2013 / ATIS-0600015.03.2013
Rectifier	ATIS-0600015.2013 / ATIS-0600015.04.2010
Wireline Access	ATIS-0600015.2013 / ATIS-0600015.07.2013
Small Network Equipment	ATIS-0600015.2013 / ATIS-0600015.08.2014
Base Station	ATIS-0600015.2013 / ATIS-0600015.09.2015
Inverter	ATIS-0600015.2013 / ATIS-0600015.10.2015
All others	Per this TPR

Note – For equipment types not specifically addressed in this TPR, please contact the author of this document for further discussion.

6.1 ATIS Correction Factors

In order to align the ATIS TEER values with the Verizon Pass/Fail requirements, perform the following correction factor to the ATIS TEER value to obtain the Verizon TEEER value.

Table 2: Correction Factor

Equipment Type	Correction Factor
Server	ATIS TEER / 10
Transport	$-\log(1 / (\text{ATIS TEER} * 1000000))$
Router and Ethernet Switch	$-\log(1 / (\text{ATIS TEER} * 1000000))$
Rectifier	ATIS TEER / 100
Wireline Access	Report ATIS TEER
Small Network Equipment	Report ATIS TEER
Base station	Report ATIS TEER
Inverter	ATIS TEER / 100

7.0 GENERAL CONDITIONS FOR MEASUREMENT

7.1 General

Testing is to be performed at or witnessed by a Verizon approved ITL as found on the Verizon NEBS webpage www.verizonnebs.com.

7.2 Environmental Criteria

7.2.1 Temperature

The equipment shall be evaluated at a temperature of $25^{\circ}\text{C} \pm 3^{\circ}\text{C}$

7.2.2 Humidity

The equipment shall be evaluated at a relative humidity of 30% to 75%

7.2.3 Pressure

The equipment shall be evaluated at site pressure between 1060 to 812 mbar

7.3 Test Equipment and Set-up

Power measurements shall be made with a suitably calibrated voltmeter and ammeter, or power analyzer. The power measurement instrument shall have a resolution of $\pm 1\%$ or better for active power. Power measurements shall be taken immediately adjacent to the powered product being evaluated. Support equipment shall be provided to verify proper operation of the equipment under test.

7.4 Test Voltage

7.4.1 DC Powered Equipment

The input to the EUT shall be at a DC voltage of $-53\text{V} \pm 2.0\text{V}$.

Equipment using voltages other than -48Vdc shall be evaluated at 2% of its nominal voltage.

7.4.2 AC Powered Equipment

The input to the EUT shall be the specified voltage $\pm 1\%$ and the specified frequency $\pm 1\%$.

8.0 MEASUREMENT APPROACH

8.1 Utilization Conditions

EUT shall be configured as a typical installation for Verizon. The equipment shall be fully loaded with all card slots populated with functioning modules and all redundancies in place. The equipment shall have all cables installed as in a typical deployment. All system functions or features that increase power consumption shall be activated during testing. If the equipment has any energy saving features that are controlled by internal software then they should be enabled for testing. The EUT shall be tested at the following utilization conditions unless specified otherwise:

Table 3: Utilization Conditions for EUT

Percentage of Utilization	
Utilization Condition 1	100%
Utilization Condition 2	50%
Utilization Condition 3	0%

Utilization Condition 1 shall be defined by the equipment manufacturer and based on the type of equipment to represent a 100% duty cycle.

Utilization Condition 2 shall represent a 50% duty cycle.

Utilization Condition 3 shall represent a 0% duty cycle. The equipment will be powered but performing no useful work (idle/sleep mode).

*Note – For mechanized distributing frames, please refer to the utilization conditions in their corresponding sections.

8.2 Testing Sequence

With the equipment configured as stated above, the EUT shall be operated at 100% utilization for at least 15 minutes prior to conducting power measurements.

After the 15 minute initialization period, the EUT input power shall be monitored as outlined in Section 7.3 to assess the stability of the EUT. If the power level does not drift by more than 5% from the maximum value observed, the EUT can be considered stable and the measurements can begin.

With the equipment operating under normal maximum power conditions, record the average input power to the equipment under test over a 15-minute time period for Utilization Condition 1. This value shall be recorded as P_{max} .

Repeat power input measurements for Utilization Condition 2 and Utilization Condition 3 and record these values at P_{50} and P_{sleep} respectively.

The total power consumption for the EUT shall be represented by the weighting formula

$$P_{Total} = (0.35 \times P_{max}) + (0.4 \times P_{50}) + (0.25 \times P_{sleep})$$

Where P_{max} is the average power measured during Utilization Condition 1, P_{50} is the average power measured during Utilization Condition 2 and P_{sleep} is the average power measured during Utilization Condition 3.

8.3 Weighting Values

Verizon assigned weighting values to accommodate for the variable utilization of equipment in each duty cycle. Because typical telecommunications equipment in the field does not run at a constant duty cycle rate it was necessary to assign the values in the weighting formula listed in Section 10.2. Each weighting has been assigned a specific

value based on Verizon's knowledge and experience of the operations of telecommunications equipment within its network. Typical Switching equipment runs nearest to the 50% utilization point and thus was given the greatest weighting in the formula. Although most telecommunications equipment does not have an idle/sleep mode, a relatively high weighting value was given as this may be the area of greatest savings in terms of reduced power consumption.

8.4 Power Equipment - Converter

8.4.1 General

Equipment is to be configured as would be for a typical Verizon deployment. Input power measurements shall be taken immediately adjacent to the input terminals. Output measurements shall be taken from the main output distribution bus. Breakers and fuses shall not be included for the calculations and measurements.

8.4.2 Power Utilization Levels

Converter Equipment testing will be performed at utilization levels of 100% and 50%.

$$P_{\text{Out Total}} = (P_{\text{Out max}} + P_{\text{Out 50}})/2$$

$$P_{\text{In Total}} = (P_{\text{In max}} + P_{\text{In 50}})/2$$

8.5 Mechanized Distributing Frames

8.5.1 Power Utilization Levels

Mechanized Distributing Frame testing will be performed at utilization levels of P_{idle} and P_{active} .

$$P_{\text{Total}} = (0.75 \times P_{\text{idle}}) + (0.25 \times P_{\text{active}})$$

Where P_{idle} is the total consumed power over a 1 hour period and P_{active} is the total power consumed over a 1 hour period while making 50 cross connections. Power measurements are to be in kWh.

9.0 TEEER FORMULATION

9.1 TEEER Formulas

The total average power, P_{Total} , calculated from above, will be used in the calculation of the TEEER. Using the type of equipment that most closely resembles the equipment tested calculate the TEEER for the given system.

Table 4: TEEER Formulas

Equipment Type	TEEER Formula
Soft Switch	$-\log(P_{Total} / BHCA)$
Media Gateway	$-\log(P_{Total} / \text{Throughput})$
Video Multiplexer - DCM	$-\log(P_{Total} / \text{Throughput})$
Mechanized Distributing Frames	$-\log(P_{Total} / \# \text{ of input connections})$

Note: Round the TEEER value to the nearest hundredth decimal point

The TEEER value calculated as described above is a number that represents an energy efficiency rating.

9.2 Verizon's Minimum TEEER Pass/Fail Requirements

The TEEER value calculated from above or derived through the ATIS testing shall meet the minimum TEEER value allowable as defined in Table 5.

The below pass/fail criteria are based on averages of typical equipment located in Verizon equipment spaces with an additional 20% improvement value.

Table 5: Pass/Fail Criteria

Equipment Type	Minimum TEEER Allowable
Transport	7.54
Optical and Video	7.54
Point-to-Point Microwave	5.75
Switch/Router	7.67
Soft Switch	2.75
Media Gateway	6.54
Video Multiplexer	6.80
Access	TBD
Power	9.20
Rectifier	9.20
Converter	9.10
Inverter	9.00
Small Network Equipment	TBD
Mechanized Distributing Frames	4.01
Server	6.53
Base Station	TBD

10.0 CPE EQUIPMENT

10.1 Set-Top Boxes

Set-Top Box equipment efficiency shall follow the methods and procedures of the most current version of the ENERGY STAR[®] requirements for Set-Top Boxes. ENERGY STAR[®] requirements for Set-Top Boxes can be found at the following website (www.energystar.gov).

10.2 AC-DC Power Supplies

AC-DC Power Supply efficiency shall meet Level VI as required by the US Department of Energy starting February 10, 2016. Efficiency requirements for AC-DC Power Supplies can be found at the following website (www.energy.gov).

11.0 EFFECTIVE DATE

This TPR has been in effect since June 5, 2008.

12.0 TEST REPORT

A test report shall be prepared that contains all necessary information:

- Date and location of test
- Physical equipment configuration
- Software Version operating on system
- Equipment physical dimensions
- Activated features and functions during testing
- Non-activated features and functions during testing
- Explanation of configuration chosen/tested
- Description of equipment's functionality verification
- Support equipment used to verify operation of equipment
- Description of test equipment used for making measurements with calibration dates
- Deviations from standard
- Duration of input energy measurement
- P_{idle} , P_{max} , P_{50} and P_{Total}
- Telecommunication Equipment Energy Efficiency Rating (TEEER)
- All recorded test data

A sample Test Report Format can be found on the following pages.

Appendix A

Verizon TEEER Compliance Report

CUSTOMER NAME:

Company Name
Company Address
Company City, State

PRODUCT:

Product Name
Product Model Number

TESTED TO:

Verizon Technical Purchasing Requirement
VZ.TPR.9205, Issue 1, June 5, 2008

Date:
Report Number:

**VERIZON INDEPENDENT TESTING
LABORATORY**

XYZ Lab
Address
City, State

Issued By: _____

Date: _____

Lab Director: _____

Date: _____

Executive Summary

The **Vendor Name, Equipment Name, Model Number**, as submitted, was evaluated to VZ.TPR.9205, Telecommunications Energy Efficiency Rating, Issue 1. The **Equipment Name, Model Number** was found to have a TEEER of **X.XX**. The **Equipment Name, Model Number** conforms/does not conform to the requirements of VZ.TPR.9205.

Test Data

Product:	
Vendor:	
Test Technician:	
Test Location:	
Test Date:	

TEEER:	
P_{Total} :	
P_{max} :	
P_{50} :	
P_{Sleep} :	
Throughput, Forwarding Capacity or Access Lines:	

Equipment Under Test	
Hardware Configuration	
Slot 1:	
Slot 2:	
Slot 3:	
Slot N:	
Equipment Dimensions	
Height:	
Width:	
Depth:	
Software	
Firmware version:	
Activated Features or Functions:	Disabled Features or Functions

Environmental Test Conditions		
Criteria	Start of Test	End of Test
Start Time		
Ambient Temperature:		
Humidity:		
Pressure:		
Feed Voltage:		
Supply Current:		
Test Equipment		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Support Equipment		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		
Hardware Vendor:		
Model:		
Serial Number:		
Calibration Date:		

Calculations:

Other Notes:

Photos of Test Set-up:

Appendix B

Examples of TEEER Formulations

Media Gateway

Throughput = 980 Gbps

$P_{\max} = 300 \text{ W}$

$P_{50} = 280 \text{ W}$

$P_{\text{sleep}} = 250 \text{ W}$

$P_{\text{Total}} = (0.35 \times 300) + (0.4 \times 280) + (0.25 \times 250) = 279.5 \text{ W}$

$\text{TEEER} = -\log (P_{\text{Total}} / \text{Throughput})$
 $= -\log (279.5 / 980,000,000)$
 $= -\log (0.0000002852)$
 $= 6.54$