

Verizon NEBSTM Compliance: Fuel Cell Systems NEBS Test Requirements

Verizon Technical Purchasing Requirements
VZ.TPR.9801
Issue 2, November 2011





CHANGE CONTROL RECORD:

| Version | Date | Action* | Reason for Revision |
|-----------------------|-----------------|---------|---|
| 1 | 01/10/2007 | Reissue | New template format. Original document issued Aug 11, 2004. |
| 2 | 11/17/11 | Change | Minor editorial updates |
| | | | |
| | | | |
| | | | |
| * New, Add, Delete, C | Change, Reissue | | |

Trademark Acknowledgement – NEBS is a trademark of Telcordia Technologies, Inc.



PREPARED BY:

| Name, Title, Organization | Date |
|--|--------------|
| Todd Talbot | Nov 17, 2011 |
| Distinguished MTS, NEBS, Fiber and Energy Efficiency | |
| Verizon Corporate Technology | |
| Systems Integration and Testing | |
| 320 St. Paul Place, Floor 14 | |
| Baltimore, MD 21202 | |
| Phone: 410-736-5945; Fax: 410-736-5144 | |
| Email: todd.f.talbot@verizon.com | |

APPROVED BY:

| Name, Title, Organization | Date |
|--|--------------|
| Howard Davis | Nov 17, 2011 |
| Manager, NEBS, Fiber and Energy Efficiency | |
| Verizon Corporate Technology | |
| Systems Integration and Testing | |
| 320 St. Paul Place, Floor 14 | |
| Baltimore, MD 21202 | |
| Phone: 410-736-5906; Fax: 410-736-5144 | |
| Email: howard.davis@verizon.com | |



Table of Contents

| 1.0 | PURPOSE | 5 |
|-----|------------------------|---|
| | SCOPE | |
| | REFERENCES | |
| | ABBREVIATIONS | |
| | DEFINITIONS | |
| | GENERAL REQUIREMENTS | |
| | PASS/FAIL REQUIREMENTS | |
| | TEST REQUIREMENTS | 7 |



1.0 PURPOSE

To better manage network energy, Verizon is deploying alternative energy sources such as stationary fuel cell systems, which produce electricity as a result of electrochemical energy conversion. Typically, these "green" energy sources provide electricity to network equipment and central offices. While these systems pose cost benefit to Verizon they must be assessed for NEBS compliance prior to installation in the network.

As with other products that serve the network, fuel cell systems shall be tested to determine their safety, performance, and reliability characteristics. The supplier shall provide a production sample to a Verizon-approved Independent Testing Laboratory (ITL) for testing and shall furnish the test results to Verizon's NEBS and Quality Assurance team for review. In addition to NEBS testing, fuel cell systems shall comply with all applicable local, state and federal statutes and regulatory requirements prior to general deployment.

2.0 <u>SCOPE</u>

This document defines the NEBS test requirements for stationary fuel cell systems, which may be deployed in Verizon's outside plant network. The "punchlist" of tests contained herein shall be used by equipment suppliers and the Verizon-approved Independent Test Laboratory as the baseline of tests to create the NEBS test plan. In all instances of test planning and test execution, the most recent and accepted versions of the GR standards shall be used.

3.0 <u>REFERENCES</u>

| GR-63-CORE | NEBS TM Requirements: Physical Protection | |
|---------------------------|---|--|
| GR-78-CORE | Generic Requirements for the Physical Design and | |
| | Manufacture of Telecommunications Products and Equipment | |
| GR-1089-CORE | Electromagnetic Compatibility and Electrical Safety - Generic | |
| | Criteria for Network Telecommunications Equipment | |
| GR-487-CORE | Generic Requirements for Electronic Equipment Cabinets | |
| VZ.NEBS.TE.NPI.2004.015 | Telecommunications Carrier Group NEBS Compliance | |
| | Checklist | |
| SIT.NEBS.RQS.NPI.2004.019 | Verizon Communications NEBS Compliance Clarification | |
| | Document | |



4.0 <u>ABBREVIATIONS</u>

| CO | Central Office | | |
|------|--|--|--|
| CPE | Customer Premises Equipment | | |
| EUT | Equipment Under Test | | |
| DOT | Department of Transportation | | |
| DOE | Department of Energy | | |
| FCC | Federal Communications Commission | | |
| FOC | Fiber Optic Component | | |
| ITL | Independent Testing Laboratory | | |
| NEBS | Network Equipment Building Systems | | |
| NEC | National Electrical Code | | |
| TCP | Testing Certification Program | | |
| TCWP | Testing Certification Witnessing Program | | |

5.0 **DEFINITIONS**

THIS SECTION INTENTIONALLY LEFT BLANK.

6.0 GENERAL REQUIREMENTS

Test configuration: The Equipment Under Test (EUT) shall be fully configured and performing its designated functions during the application of NEBS testing. All chemical fuels, telecommunication lines, connection hoses, sensors, documentation (installation and operating manuals), mounting and grounding schemes shall be provided to the test laboratory by the supplier prior to test commencement. Because of the volatility of the chemical energy source (i.e., hydrogen, natural gas, etc.), special safety considerations shall be in place before test commencement.

In addition to the specific test requirements listed below, products must comply with GR-78-CORE, Generic Requirements for the Physical Design and Manufacture of Telecommunications Products and Equipment. Vendors may self-declare their product's compliance to GR-78-CORE by submitting a completed copy of Appendix B of the Telecommunication Carrier Group Checklist. Current versions of the TCG Compliance Checklist and the Verizon NEBS Clarification document can be found on the Verizon web page (http://www.verizonnebs.com/index.html#chklist). A list of approved Verizon ITLs can be found on the Verizon NEBS Compliance web page, http://www.verizonnebs.com/tcppage.html.

7.0 PASS/FAIL REQUIREMENTS



The EUT shall be configurable as documented in the manufacturer's installation procedures and shall operate reliably over its intended life cycle. The product shall operate as intended during immunity and susceptibility testing (EMI, Operational Temperature and Relative Humidity, Altitude, etc.,) and the test report shall include failure thresholds, if any, so that proper risk analysis can be made. The product shall meet all defined limits in the NEBS standards and the references listed above. Lines, hoses, clamps and couplers shall be continuously monitored for pressure leaks during fire resistance and seismic testing. Any degradation in pressure during or immediately following the application of these tests shall be considered a failure.

8.0 TEST REQUIREMENTS

GR-63-CORE, NEBS Requirements: Physical Protection

| Section | Test | Configuration |
|---------|--|--|
| 2 | Spatial | Non-functioning unit. Inspection only. |
| 4.1.1.1 | Low-Temperature Exposure and Thermal Shock | As configured for shipment |
| 4.1.1.2 | High-Temperature Exposure and Thermal Shock | As configured for shipment |
| 4.1.1.3 | High Relative Humidity Exposure | As configured for shipment |
| 4.1.2 | Operating Temperature and Relative Humidity (see Note 1) | Fully functional system |
| 4.1.3 | Altitude (see Note 2) | Fully functional system |
| 4.5 | Airborne Contaminants | Fully functional system |

NOTE 1:

The following excerpt is taken from the Verizon NEBS webpage. It explains how to conduct the Operating Temperature and Relative Humidity test of GR-63-CORE with a modification to the temperature profile to address outside plant equipment testing. As expressed in GR-63-CORE, the temperature profile is consistent with that found in the central office environment. By incorporating a wider temperature range, however, outside plant equipment can be tested to an operational temperature and relative humidity cycle consistent with normal operating conditions found in the outside plant.

The purpose of this memo is to clarify the Operating Temperature/Relative Humidity testing methodology for cabinets used to house electronic equipment in the Outside Plant (OSP). It will also ensure compliance with the requirement limits as specified in GR-487-CORE Generic Requirements for Electronic Equipment Cabinets section 2.2 (Operating Environment).

The current version of GR-487-CORE does not provide a detailed test methodology for performing Operating Temperature/Relative Humidity of cabinets with installed electronic equipment. This omission in the Generic Requirement document causes independent test laboratories (ITLs) and equipment providers to interpret the test methodology (duration/profile) differently. Inconsistently applied test methods become the source of unreliable product testing.

Verizon requires the test methodology specified in GR-63 be used with the temperature and humidity criteria of GR-487-CORE Section 3.26. In order to apply the OSP equipment standards



to the central office test methods, note the following:

- a) Replace the CO temperature limits in GR-63-CORE with the ambient temperature limits of GR-487, -40 °C to +46 °C, with solar loading applied only at +46 °C or +65 °C for [environmentally controlled] enclosures without solar loading, as specified in GR-487 section 3.26 requirements. ITLs will report results by including a pictorial representation of the temperature profile.
- b) The equipment, in a configuration representing planned deployment, will operate under the above conditions for two consecutive failure-free cycles. ITLs will report results by including how many cycles were run for the equipment to pass.

NOTE 2:

Verizon has reviewed its policy with respect to Altitude testing per GR-63-CORE and now accepts altitude test results using the temperature compensation method for products that have no mechanical sensitivities. Mechanical sensitivities include items such as hard disk drives, sealed relays, fuel cells, or other items that may be mechanically affected by a change in differential pressure.

Verizon will now accept any of the following three methods for demonstrating compliance to the NEBS Altitude Test criteria.

- 1. The ITL shall follow Option 1 test sequences of Section 5.1.3, using a hypobaric chamber.
- 2. The ITL shall follow Option 1 test sequences in Section 5.1.3, using the temperature compensation method to simulate lower atmospheric pressures, according to the rule of +1° C per 1000 feet increase in altitude. For example, if a test temperature should be 50° C and test pressure should be 80 kPa, then the temperature compensation method would require exposing the EUT to 56° C.
- 3. The ITL shall test to Objective O4-11[137], and if the EUT passes, it is considered to meet NEBS criteria R4-8, R4-9, and O4-12. The chamber temperature shall be increased to 61° C (shelf equipment) or 56° C (frame equipment), at a ramp rate of 30° C/hour. After an eight-hour dwell at this temperature, the chamber temperature shall be decreased at a rate of 30° C/hour to ambient temperature. If using this abbreviated form of the Altitude Test, Verizon will accept the test running concurrently with the Operational Temperature and Humidity Test. To integrate these tests, the parameters for the shortened Altitude Test (61° /56° C for 8 hours) will be used during Step 3 of the Operational Temperature and Humidity Test (see Figure 5-4, GR-63). Step 3 must continue to maintain a minimum 12 hour dwell of at least 50°C and no more than 32% RH. However, functional degradation of the EUT during the high temperature extreme will be considered a failure of both tests.

The EUT shall continue to be functional throughout the Altitude Test, regardless of the test method used. Option 2 of section 5.1.3 remains unacceptable to Verizon for altitude testing, as it does not demonstrate conformance to Objective criteria.



GR-1089-CORE Electromagnetic Compatibility (EMC) and Electrical Safety – Generic Criteria for Network Telecommunications Equipment

| Section # | Test | Configuration |
|-----------|---|------------------------------|
| 2 | ESD | Fully functional system |
| 3.2.1 | Radiated Emissions (Electric Fields) with Cabinet doors open [tested to cabinet doors closed limit) | Fully functional system |
| 3.2.2 | Radiated Emissions - Magnetic Fields | Fully functional system |
| 3.2.3 | Conducted Emissions – AC Power Leads (Voltage) | Fully functional system |
| 3.2.4 | Conducted Emissions – AC and DC Power & Signal Leads (Current) | Fully functional system |
| 3.2.5 | Conducted Emissions – Analog VoiceBand Leads) | Fully functional system |
| 3.3.1 | Radiated Immunity (Electric Fields) with Cabinet Doors and Covers Closed | Fully functional system |
| 3.3.2 | Radiated Immunity (Electric Fields) with Cabinet Doors and Covers Open | Fully functional system |
| 3.3.3 | Conducted Immunity (AC and DC Power Ports and Signal Leads) | Fully functional system |
| 4.2.1 | Voltage-Limiting Protectors | Fully functional system |
| 4.2.2 | Current-Limiting Protectors | Fully functional system |
| 4.2.3 | Fuse Links | Fully functional system |
| 4.3 | Lightning Surges – Longitudinal & Metallic | Fully functional system |
| 4.4 | AC Power Faults (contact & fault induction from power lines to telecom ports) | Fully functional system |
| 4.5.3 | Listing Requirements | Fully functional system |
| 4.5.4 | Short Circuit Tests (Telecommunications Port) | Electronics operational only |
| 4.5.7 | First-Level Lightning Surge (Telecommunications Port) | Fully functional system |
| 4.5.8 | Second-Level Lightning Surge (Telecommunications Port) | Fully functional system |
| 4.5.11 | Current-Limiting Protector Tests (Telecommunications Port) | Fully functional system |
| 5 | Steady State Power Induction | Fully functional system |
| 7 | Electrical Safety Criteria | Fully functional system |
| 9 | Bonding and Grounding Inspection | Fully functioning system |



GR-487-CORE Generic Requirements for Electronic Equipment Cabinets

| Section # | Test | Configuration |
|---|---|--------------------------|
| 3.1 - Product Samples | R3-1, R3-2, R3-3 | Fully functioning system |
| 3.2 - Product Changes | R3-4 | |
| 3.3 - Safety & Reliability Considerations | R3-5, R3-6, R3-7, R3-8, R3-9 | Fully functioning system |
| 3.4 - Metallic Materials | | Fully functioning system |
| 3.5 - Polymeric and other Non-Metallic Materials | CR3-13 – Polymetric identification | |
| | R3-25 - Adhesives Qualities R3-26, R3-27, R3-28, R3-29, R3-30, R3-31, R3-32, R3-33, R3-34, R3-35 | Cabinet only |
| 3.7 - Screens and Filters | R3-36, R3-37, R3-38, R3-39 | Cabinet only |
| 3.8 - Door Restraints – Vertical | R3-40, R3-41, R3-42, R3-43, O3-44 | Cabinet only |
| | R3-45, R3-46, R3-47, R3-48, R3-49, R3-50, R3-51, R3-52, R3-53, R3-54, CR3-55, R3-56 | Cabinet only |
| 3.10 – Lifting Details | R3-57, R3-58, R3-59 | Cabinet only |
| 3.11 – Security | R3-60, O3-61, CR3-62, CR3-63, R3-64, CR3-65, R3-66, R3-67, CR3-68, CR3-69 | Cabinet only |
| 3.12.1 – Alarms | | Fully functional system |
| 3.12.2 – Engine-Generators | | If applicable |
| 3.13 – Condensation | R3-81, R3-82 | Fully functional system |
| 3.14 – Fans | R3-83, O3-84, O3-85, O3-86, R3-87 | Fully functional system |
| 3.15 – Bonding and Grounding | R3-88, R3-89, R3-90, R3-91 | Fully functional system |



| 3.16 – AC Power (Commercial and Auxiliary) | R3-92 – CR3-109 | If applicable |
|--|---|-------------------------------------|
| 3.17 – Splicing Compartment | R3-110 – CR3-123 | If applicable |
| 3.18 - Electronic Equipment Compartment | R3-124, CR3-125, R3-126 | Fully functional system |
| 3.19 – Battery Compartment | R3-127 – R3-138 | If applicable |
| 3.20 – Engine-Generator Compartment | R3-139 – R3-152 | If applicable |
| | R3-153 – R3-156 | If applicable |
| 3.22 – Documentation | R3-157 – CR3-159 | Fully functional system |
| 3.23 –Marking, Packaging, and Shipment | R3-160 – R3-167 | Fully functional system |
| 3.24 - Installation and Maintenance | R3-168 – CR3-184 | Fully functional system |
| 3.25 – Quality | R3-185, R3-186 | Fully functional system |
| 3.26 – Exposure to High Temperature | R3-187, CR3-188, CR3-189, CR3-190 | Fully functional system |
| 3.27 – Thermal Shock | R3-191 | Cabinet only, with functioning fans |
| 3.28.1 – Wind Driven Rain | R3-192 | Cabinet only, with functioning fans |
| 3.28.2 – Rain Intrusion | O3-193 | Cabinet only, with functioning fans |
| 3.28.3 – Lawn Sprinklers | O3-194 | Cabinet only, with functioning fans |
| 3.28.4 - Weather Tightness | R3-195 | Cabinet only, with functioning fans |
| 3.29 - Acoustic Noise Suppression | R3-196 | Fully functional system |
| 3.30 – Wind Resistance | R3-197 (Applies to pole or wall mounted equipment) R3-198 | Cabinet only |
| 3.31 – Impact Resistance | R3-199 | Cabinet only |
| 3.32 – Firearms Resistance | R3-200 R3-201; NA | Cabinet only |
| 3.33 – Fire Resistance (see Note 3) | R3-202 | Fully Functional system |
| 3.34 – Corrosion Resistance (3.34.1 - Salt Fog) | R3-203 | Cabinet only, with functioning fans |
| 3.34.2 – Temperature Cycling /High Humidity | R3-204 | Cabinet only, with functioning fans |
| 3.35.1 – Transportation Shock (per GR-63, sec 5.3.3) | R3-205 | Fully functional system |
| 3.35.2 – Transportation Shock (Rail) | CR3-206 | Fully functional system |
| 3.35.3 – Transportation Vibration (per GR-63, sec 5.3.3) | R3-207 | Fully functional system |



| 3.35.4 – Installation Shock (per GR-63, sec 5.3.2) | R3-208 | Fully functional system |
|---|---------|--|
| 3.35.5 – Environmentally Induced Vibration (per GR-63, sec 5.4.2) | CR3-209 | Fully functional system |
| 3.35.6 – Earthquake Resistance (per GR-63, sec 4.4.1.2 and 4.4.1.3) | | Fully functional system with anchoring mechanism |

NOTE 3:

Fuel line pressure shall be continuously monitored during fire resistance and seismic testing. Any degradation in line pressure during or immediately following the application of these tests shall be considered a failure.